

Tutorial: How to connect to Romania NXDN Network from WPSD

The screenshot shows the 'WPSD Digital Voice - Configuration' interface. At the top, it says 'Hostname: yo6say' and '16:27:56, Jul 18'. There are navigation links for 'Dashboard', 'Admin', 'Power', 'Advanced', and 'WPSD Update'. The 'General Configuration' section is highlighted, showing a table of settings:

Field	Value	Notes
Hostname:	yo6say	⚠ Do not add suffixes such as ".local", etc. Note: A reboot is required for this change to take effect.
Node Callsign:	YO6SAY	⚠ Do not add suffixes such as "-G"
DMR/CCS7 ID:	2260358	📌 Required for DMR Mode & DMR Cross-Modes (If you don't have one, get a DMR ID from RadioID.Net)
NXDN ID:	8227	📌 Required for NXDN Mode & NXDN Cross-Modes (If you don't have one, get an NXDN ID from RadioID.Net)

1. In "General Configuration" set your NXDN ID.
You can find your NXDN ID [here](#). In my case is 8227.

YO6SAY 

Silviu
Corona,
Romania

Membership Status: Not a member! ([Subscribe Now!](#))


Things your missing out on by not being a member!

- [Contacts Generator](#)
- [Buddy Watch/On Air Alerts](#)
- [Buddy Mail - Securely Message Other Users](#)
- Flagged as a **Member** in **Support portal** and **Public Profile**
- Subscriptions help RadioID Pay the Bills!
- Plus New Exciting Future Additions!


Your Radio ID's							
Radio ID	Callsign	Remarks	Type	Last Heard ⓘ	Last TG	Expires	Status
2260358	YO6SAY	DMR	DMR / P25 / CCS7	2024-07-12 18:35:04	226	Does not expire	Approved
8227	YO6SAY	NXDN	NXDN	--	--	Does not expire	Approved
2260358[nn]	YO6SAY	--	HOTSPOT ⓘ	--	--	--	Approved

- If you don't have an NXDN ID, you can request one from here:
https://radioid.net/register/reg_nxdn


2. From “Radio/MMDVMHost Modem Configuration” > “Radio Cross-Modes” enable “**DMR2NXDN**” option




3. From “NXDN Configuration”, select the preferred Talk Group for Romania NXDN reflector.



3.1. Set the “NXDN RAN” to 1



4. Save the configuration



5. Program the channel in your radio (TS2)

For example, TG 226 can be accessed as 7000226
TG 2261 can be accessed as 7002261